Air Disinfecting Purifier-70 (ADP-70)

Instruction & Installation Manual



SPECIFICATIONS

DIMENSIONS

10.25"H x 9.75"W x 3.75"D

ELECTRICAL

Unit Operates on: 115 VAC (24 VDC) provided power supply

WEIGHT

Wall Mount Version: 2.7 lbs.

WARNINGS

** Electrical shock may occur. Hard-wired Installations should be handled by a licensed professional.

** Never service the unit while it is connected to a power source. Electrical shock or injury may occur.

** A slight odor may be noticeable when the unit is first installed and operated. This is due to the newness of the UV bulb being used and the initial cleaning of the contaminated space. The odor is completely harmless.

INSTALLATION (2000 sq ft coverage for an open room)

- 1. Determine location for desired placement of unit. Typically, the angled grill should be pointed upward and mounted as high on the wall as desired (higher the better).
- 2. Make access available for 115 VAC connection.
- 3. Option If utilizing the LED operation indicator light then determine where the light should be located and how to run the line from the unit to that location. Connect the LED lead to the connection from the back of the Atmos-3 unit.
- 4. Once securely mounted plug in provided power supply and unit is in service.

MAINTENANCE

******ALWAYS UNPLUG POWER SOURCE BEFORE SERVICING UNIT******

Cleaning

The unit should be cleaned occasionally to ensure proper operation.

- 1. Remove the Cover Plate from the unit.
- 2. Wipe everything down with a damp cloth.
- 3. Replace the Cover Plate of the unit.

Replacing the Filter

We recommend washing the Filter every 90 days or when noticeably contaminated.

- 1. Remove the Filter Cover Plate from the unit.
- 2. Remove the Filter
- 3. Wash filter thoroughly with mild soap/detergent and water.
- 4. Replace with the cleaned (or new Filter) purple side facing in/red side

out.

5. Replace the Filter Cover Plate.

Replacing the PCO Cell

Your Purifying <u>Cell should be replaced every 2 years</u>.

- 1. Remove the Cover Plate from the unit.
- 2. Locate the UV Cell and press the tab away from it.
- 3. Slide the UV Cell towards its Power Plug and pull it out of the slot.

4. Disconnect the power to your old UV Cell and replace it with your new UV Cell. Ensure plug is fully seated on UV Lamp Pins.

5. Place the end opposite the power source in first and press the UV Cell into place, allowing the tab to secure it.

6. Replace the Cover Plate.

Disposal of the Cell and UV Lamp

DO NOT THROW YOUR UV CELL IN THE TRASH.

Dispose of the spent Cell and UV Lamp at your local recycling center.

Hg-LAMP CONTAINS MERCURY. Manage in accordance with disposal laws. (Visit www.lamprecycle.org for proper instructions.)

TROUBLESHOOTING

1. Cell Doesn't Turn On

• Check for secure connection. • Try another Cell. • Ballast needs replaced.

2. Fan Doesn't Turn On

• Check for secure connection. • Fan needs replaced.

WARRANTY

WARRANTY LIMITED WARRANTY INFORMATION

YOUR ADP-70 (PRODUCT) AND PCO CELL ARE EACH WARRANTED TO BE FREE FROM ALL DEFECTS IN MATERIAL AND WORKMANSHIP IN NORMAL USE FOR A PERIOD OF **(1) ONE YEAR** FROM DATE OF PURCHASE. THE WARRANTY IS GRANTED ONLY TO THE ORIGINAL PURCHASER. THE WARRANTY IS SUBJECT TO THE FOLLOWING PROVISIONS:

ANY DAMAGES OR MALFUNCTIONS CAUSED BY NEGLIGENCE, ABUSE, OR USE NOT IN ACCORDANCE WITH THE PRODUCT OWNER'S MANUAL ARE NOT COVERED BY THIS WARRANTY. LIKEWISE, ANY DEFECTS OR DAMAGES CAUSED BY UNAUTHORIZED SERVICE OR THE USE OF OTHER THAN GENUINE O-So Pure PARTS ARE NOT COVERED.

O-So Pure WILL, AT ITS OPTION, REPAIR OR REPLACE A DEFECTIVE PRODUCT OR PART(S) FOR THE PRODUCT THAT IS/ARE COVERED BY THIS WARRANTY. AS A MATTER OF WARRANTY POLICY, O-So Pure WILL NOT REFUND THE CUSTOMER'S PURCHASE PRICE.

OBTAINING WARRANTY SERVICE

TO OBTAIN WARRANTY SERVICE YOU MUST RETURN THE DEFECTIVE PRODUCT ALONG WITH PROOF OF PURCHASE TO THE O-So Pure AUTHORIZED SERVICE CENTER. ALL SHIPPING COSTS SUBMITTED UNDER THIS WARRANTY SHALL BE BORNE BY PURCHASER. UNLESS THIS WARRANTY IS EXPRESSLY RENEWED OR EXTENDED BY O-So Pure, ANY REPAIRED OR REPLACED PART OF UNIT SHALL BE WARRANTED TO THE ORIGINAL PURCHASER ONLY FOR THE LENGTH OF THE UNEXPIRED PORTION OF THE ORIGINAL WARRANTY.

BEFORE ANY PRODUCT IS SENT FOR SERVICE, THE CUSTOMER SHOULD CONTACT THE O-So Pure SERVICE CENTER TO OBTAIN A RETURN MERCHANDISE AUTHORIZATION (RMA) NUMBER. THIS RMA NUMBER SHOULD BE CLEARLY WRITTEN ON THE BOX BEFORE SHIPPING. ALL COMPONENTS/PARTS INCLUDING THE REMOTE (IF APPLICABLE), MANUALS, AND ORIGINAL PACKAGING SHOULD BE INCLUDED IN THE RETURN IF AVAILABLE.

ANY WARRANTY THAT MAY BE IMPLIED IN CONNECTION WITH YOUR PURCHASE OR USE OF THE PRODUCT, INCLUDING ANY WARRANTY OF MERCHANTABILITY OR ANY WARRANTY FOR FITNESS FOR A PARTICULAR PURPOSE IS LIMITED TO THE DURATION OF THIS WARRANTY. SOME STATES DO NOT ALLOW LIMITATIONS ON HOW LONG AN IMPLIED WARRANTY LASTS, SO THE ABOVE LIMITATIONS MAY NOT APPLY TO YOU.

YOUR RELIEF FOR THE BREACH OF THIS WARRANTY IS LIMITED TO THE RELIEF EXPRESSLY PROVIDED ABOVE. IN NO EVENT SHALL O-So Pure, BE LIABLE FOR ANY CONSEQUENTIAL OR INCIDENTAL DAMAGES YOU MAY INCUR IN CONNECTION WITH YOUR PURCHASE OR USE OF THE PRODUCT. SOME STATES DO NOT ALLOW THE EXCLUSION OR LIMITATION OF INCIDENTAL OR CONSEQUENTIAL DAMAGES, SO THE ABOVE LIMITATION OR EXCLUSION MAY NOT APPLY TO YOU.

THIS WARRANTY GIVES YOU SPECIFIC LEGAL RIGHTS, AND YOU MAY ALSO HAVE OTHER RIGHTS WHICH VARY FROM STATE TO STATE.

REGISTRATION

PLEASE REGISTER YOUR PRODUCT WITHIN 10 DAYS OF PURCHASE BY calling 1-800-OSO-PURE.